

# Junistar Tube Round 3x Junistar Tube Square 3x



**III** 400mA, 36V, 15W

Junistar Tube Square: 185x95mm  
Junistar Tube Round: 184x94mm

□ 220-240V, 50/60Hz

102x51x22mm

✓ Volume: Min 4L (4000cm<sup>3</sup>)  
Ex: 300mmx300mmx48mm=4.3L  
Min 60mm  
10-40mm

✓ Multibox TEK  
Multibox Mini  
LEDbox 48

⚠

⚠

Ø: 3-7mm  
Ø: 7-11mm

● 0,5 - 1,0 mm<sup>2</sup> 8 mm  
● 1,5 - 2,5 mm<sup>2</sup> 12 mm

ca. 10° (max. 20°)  
Max. 16A

Dipswitch

|    | ON    | ON    | ON    | ON    | Standard | ON    |
|----|-------|-------|-------|-------|----------|-------|
|    | 1 2 3 | 1 2 3 | 1 2 3 | 1 2 3 | 1 2 3    | 1 2 3 |
| mA | 200   | 250   | 300   | 350   | 400      | 450   |
| lm | 50%   | 63%   | 75%   | 88%   | 100%     | -     |

⚠

Rev: 16.01.2026

**NORWAY**  
SG Armaturen AS

Skytterheia 25  
N-4790 Lillesand

Tel: +47 37 50 03 00  
firmapost@sg-as.no  
www.sg-as.no

**SWEDEN**  
SG Armaturen AB  
Tel: +46 31 81 71 10  
info@sg-ab.se  
www.sg-ab.se

**DENMARK**  
SG Armaturen A/S  
Tel: +45 70 70 72 13  
info@sg-as.dk  
www.sg-as.dk

**GERMANY**  
SG Leuchten GmbH  
Tel: +49 40 23 99 44 59  
info@sg-leuchten.de  
www.sg-leuchten.de


**FINLAND**  
SG Armaturen Oy  
Tel: +358 02 07 30 39 60  
info@sg-oy.fi  
www.sg-oy.fi

**FRANCE**  
SG Lighting SA/NV  
Tel: +33(0) 4 94 93 00 00  
info.france@sglighting.fr  
www.sglighting.net

**BENELUX**  
SG Lighting SA/NV  
Tel: +32(0) 15 20 72 71  
info.benelux@sglighting.net  
www.sglighting.net

**SWITZERLAND**  
SG Leuchten SA  
Tel: +41 44 868 20 00  
info@sg-leuchten.ch  
sg-leuchten.ch

**INTERNATIONAL**  
SG Lighting Co Ltd.  
Tel: +86 769 88 49 20 88  
cindy@sgdgc.com  
www.sg-as.com



**NO:** Skru av strømmen før montering.  
**DK:** Sluk for strømmen inden montering.  
**SE:** Stäng av strømmen innan montering.  
**EN:** Turn off power before installing.  
**FR:** Couper le courant avant l'installation.  
**NL:** Stroom uitschakelen voor u het toestel installeert.  
**DE:** Vor Installationsarbeiten den Strom abschalten.  
**FI:** Sammuta virta ennen kytkemistä

2: Replaceable (LED only)  
light source by a professional



3: Replaceable control gear  
by a professional



**NO:** Kan kun installeres og vedlikeholdes av en registrert installasjonsvirksomhet.

**DK:** Må kun installeres og vedligeholdes af uddannet elektriker.

**SE:** Skall installeras och underhållas av behörig elektriker.

**EN:** Only to be installed and maintained by an authorized electrician.

**FR:** Doit être installé et maintenu par un électricien qualifié.

**NL:** Mag alleen geïnstalleerd en onderhouden worden door een bevoegde elektricien.

**DE:** Dieses Produkt darf nur durch autorisiertes Personal (z.B. Elektro-Installateur) angeschlossen, in Betrieb genommen und gewartet werden.

**FI:** Asentaa ja huoltaa saa vain valtuutettu sähköasentaja

Ø 83mm

